


SPT-3000 SD Card & USB Module Installation Guide

Check Contents

SD Card & USB Module ▶



1 Check whether the power of PC POS system and peripherals are turned off.

2 Remove connectors for peripheral and DC power supply jack.




⚠ When DC power jack is removed, the neck of the power jack should be pulled and thus removed.




3 Remove screws, release lock-lever then finally remove system back cover, as shown in drawing.



4 Take off the speaker cable and screw from the bracket.




5 Remove original USB module by holding up the bracket.



6 Install new SD Card & USB module as shown in drawing.



7 Reconnect Speaker Cable and tighten the screw.



8 Assemble back cover cabinet, lock the lever and tighten the screw.

